

Direct replacement for Elite2 12D2/D4

### Product Specs

- RMS Power Handling: 1200W
- Impedance: Dual 2-Ohms or Dual 4-Ohms
- Mounting Depth: 7.5in - 190mm
- Mounting Diameter: 10.86in - 276mm
- 60mm of Peak to Peak Excursion
- 1200W RMS Power Handling
- 3.0" Ultra High Temp Copper Wound Voice Coil
- Removable tri-LEDs for Customization or Field Service
- Radial Backplate Venting System
- Easy Connect Single Location Speaker Terminal
- Long Throw Dual Spider Suspension
- High Excursion CAE/CAD Motor Design
- Woven Tinsel Leads
- Black Anodized Aluminum Former
- Injection Polypropylene Dustcap
- High Roll Butyl Rubber Double Stitched Surround
- Optimized for Sealed or Vented Enclosures
- Rigid Powder Coated Anti-Resonant Cast basket
- Quick Disconnect Series/Parallel Wires Included
- Red/White/Blue LED Assembly Options Included
- Designed for Sealed or Ported Enclosures



### Ti3X Subwoofers include 3 LED color options

Red

White

Blue



### Enclosure Quick Reference Chart

	Ti312d2/4X
RMS Power Handling:	1200w
Optimal RMS Power Range:	1000w-1200w
Mounting Depth (in.):	7.5
<b>SEALED</b>	
SPI (cu.ft.)	0.75
Normal (cu. ft.)	1.1
SQ (in. ft.)	1.5

	VENTED - SPL
Volume (cu. ft.)	1.75
Slot Vent Opening (in.)	2 x 12
Slot Vent Length (in.)	23.5
Tuning Freq (Hz)	38Hz

\* Subsonic filter set at 35Hz to 40Hz is highly recommended.

	VENTED - NORMAL
Volume (cu. ft.)	2.0
Slot Vent Opening (in.)	2 x 12
Slot Vent Length (in.)	24
Tuning Freq (Hz)	35Hz

\* Subsonic filter set at 35Hz to 40Hz is highly recommended.

	VENTED - SQ
Volume (cu. ft.)	2.25
Slot Vent Opening (in.)	2 x 12
Slot Vent Length (in.)	25.5
Tuning Freq (Hz)	32Hz

\* Subsonic filter set at 35Hz to 40Hz is highly recommended.

\*\* Enclosures include displacement of the driver, but do not include vent displacement

### Instructions for changing the Tri-Light LED's



Disconnect the 12v power

Remove the (3) 2.5mm allen head screws

Slowly pull up on the Tri-Light

Disconnect the connector by using a small plastic pry-tool (Never Pull on wires)