

IP68 Mini Commercial Camera User Manual



EchoMaster is a Power Brand of AMP Global EchoMaster.com



email - technical.eu@aampglobal.com (Europe)

15500 Lightwave Drive, Suite 202 Clearwater, Florida 33760



Introduction

Thank you for purchasing your EchoMaster automotive camera.

The following part numbers are supported:

- CAM-10B-P
- CAM-10B-N
- CAM-10W-P
 CAM-10W-N
- CAM-10W-N

EchoMaster cameras are designed to improve safety during driving by providing high quality images of surrounding areas and obstacles in the vicinity of the vehicle. They will also improve vehicle maneuvering capability by displaying blind spots not normally visible to the driver.

Please ensure you read and understand all aspects of this manual before fitting or using your EchoMaster Camera. Choose a suitable mounting place dependent on the application. Ensure that there are no wiring harnesses or hoses/pipes located behind this panel before drilling.


Key Features

- 1/4" CCD Sensor
- Operates at 0.5 LUX
 IP68 Bated
- IP68 Rated
 150 Degree Viewing Angle

Box Contents

- Camera
- Bracket
- Double-Sided Tape
- Mounting Hardware
- Harness
- Manual

Dimensions



Speci ications

		CAM-10W-P I CAM-10W-N CAM-10B-P I CAM-10B-N	
Sensor Type	1/4'	1/4" CCD	
LEDs		0	
Illumination	0.5	0.5 LUX	
Viewing Angle	150 c	150 degrees	
Mirror Image	Y	YES	
Normal View		NO	
Water/Debris-Proof		IP68	
Audio		NO	
Power Supply	6-3	6-30V DC	
Current	<6	<60mA	
Working Temperature	-20°C	-20°C - +70°C	
Dimensions (mm)	D (41) x W	D (41) x W (22) x H (27)	
System	PAL	NTSC	
TV Lines	420	N/A	
Resolution	680x512	N/A	

Wiring Diagram & Pin Out

